



Display type: Samsung LTA260W1-L02
 Cable no.: not available
 System: ADD-LVDSTX (-/OEM) on 886LCD/ATX family or similar

ADD-LVDS: BIOS X203 -, XU203D -, XGE- WSXGA1PO, SW1(1,2,3,4,5,6)= (on,on,x,x,x,x)
 ADD-LVDS-OEM: BIOS X203, XU203D, XGE SW1(1,2,3,4,5,6)= (on,on,on,off,on,on)

Display (31-pole conn.)		34-pole connector		Remarks
Pin no.	Function	Pin	Function	
1	VCC (Inverter)	33,34	LCDVCC	+5V
2	VDD	33,34	LCDVCC	+5V
3	VDD	33,34	LCDVCC	+5V
4	VDD	33,34	LCDVCC	+5V
5	VDD	33,34 *	LCDVCC	+5V
6	GND	8,19,20,31,32 *	GND	
7	Analog Dimming	8,19,20,31,32	GND	Backlight: GND=> max, 3.3V => min.
8	PWM Dimming	33,34 *	LCDVCC	Backlight: 30% (min) -100% (max) duty cycle (active high +3.3V to +5V)
9	Backlight on/off	33,34	LCDVCC	Active high +3.3V to +5V
10	GND	8,19,20,31,32 *	GND	
11	GND	8,19,20,31,32 *	GND	
12	RX3+	22	A3+	Pair no 5
13	RX3-	21	A3-	Pair no 5
14	GND	8,19,20,31,32	GND	
15	GND	8,19,20,31,32	GND	
16	RXCLK+	24	CLK1+	Pair no 4
17	RXCLK-	23	CLK1-	Pair no 4
18	GND	8,19,20,31,32	GND	
19	GND	8,19,20,31,32	GND	
20	RX2+	26	A2+	Pair no 3
21	RX2-	25	A2-	Pair no 3
22	GND	8,19,20,31,32	GND	
23	GND	8,19,20,31,32	GND	
24	RX1+	28	A1+	Pair no 2
25	RX1-	27	A1-	Pair no 2
26	GND	8,19,20,31,32	GND	
27	GND	8,19,20,31,32	GND	
28	RX0+	30	A0+	Pair no 1
29	RX0-	29	A0-	Pair no 1
30	GND	8,19,20,31,32 *	GND	
31	GND	8,19,20,31,32 *	GND	

* = Tested having this signal unconnected (NC)